




REZ-1T42-M2-LD

Brand Name	MARK 10 POWERLINE
Ballast Type	Electronic Dimming
Starting Method	Programmed Start
Lamp Connection	Series
Input Voltage	120
Input Frequency	60 HZ
Status	Active

Electrical Specifications

Lamp Type	Num. of Lamps	Rated Lamp Watts	Min. Start Temp (°F/°C)	Input Current (Amps)	Input Power (Watts) (min/max)	Ballast Factor (min/max)	MAX THD %	Power Factor	Lamp Current Crest Factor	B.E.F.
* CFQ26W/G24Q	1	26	50/10	0.26	08/31	0.05/1.00	10	0.98	1.6	3.23
CFTR26W/GX24Q	1	26	50/10	0.26	08/31	0.05/1.00	10	0.98	1.6	3.23
CFTR32W/GX24Q	1	32	50/10	0.32	09/38	0.05/1.00	10	0.98	1.6	2.63
CFTR42W/GX24Q	1	42	50/10	0.41	10/49	0.05/1.00	10	0.99	1.6	2.04

Wiring Diagram




Diag. 134

The wiring diagram that appears above is for the lamp type denoted by the asterisk (*)

Standard Lead Length (inches)

Enclosure



Enclosure Dimensions

OverAll (L)	Width (W)	Height (H)	Mounting (M)
4.98 "	3.00 "	1.29 "	4.60 "
4 49/50	3	1 29/100	4 3/5
12.6 cm	7.6 cm	3.3 cm	11.7 cm

Revised 08/17/2006



Data is based upon tests performed by Advance Transformer in a controlled environment and representative of relative performance. Actual performance can vary depending on operating conditions. Specifications are subject to change without notice. All specifications are nominal unless otherwise noted.

ADVANCE

O'HARE INTERNATIONAL CENTER · 10275 WEST HIGGINS ROAD · ROSEMONT, IL 60018

Customer Support/Technical Service: Phone: 800-372-3331 · Fax: 630-307-3071

Corporate Offices: Phone: 800-322-2086

Reprinted by BulbsDepot.com