
PHILIPS Lighting



SmartMate

SMARTMATE ICF2S18M1BSQS35M

Offering maximum versatility, the Philips Advance family of SmartMate ballasts for 4-pin compact fluorescent lamps drive a broad range of quad and triple-tube, circline, 2D, and long twin-tube lamps. SmartMate ballasts' energy efficient design, compact and lightweight housing, and user-friendly features make these ballasts an ideal choice for fixture manufacturers, retrofitters, and MRO replacement.

Product data

| General Information | | | | | |
|-------------------------------|------------------------|--|--|--|--|
| Lamp Type | CFQ18W/G24Q | | | | |
| Number Of Lamps | 1/2 piece/unit | | | | |
| Ballast Type | Electronic Fluorescent | | | | |
| Base Model | ICF2S18M1BSQS | | | | |
| Suitable For Outdoor Use | Yes | | | | |
| Automatic Restart | Yes | | | | |
| | | | | | |
| Operating and Electrical | | | | | |
| Input Voltage | 120 to 277 V | | | | |
| Input Frequency | 50 to 60 Hz | | | | |
| Total Harmonic Distortion USA | 10 % | | | | |
| Ignition Method | Programmed Start | | | | |
| Crestfactor (Nom) | 1.7 | | | | |
| Ignition Time (Nom) | 1.5 s | | | | |
| Ballast Factor (Nom) | 0.95 | | | | |
| Power Factor (Nom) | 0.98 | | | | |
| Input Current (Max) | 0.30 A | | | | |
| Input Current (Min) | 0.13 A | | | | |
| Input Power (Nom) | 35-35 W | | | | |
| | | | | | |


| Rated Lamp Power | 18 W | | |
|------------------------------------------|----------------------|--|--|
| | | | |
| Wiring | | | |
| Color Input Terminals | Black and White | | |
| Color Output Terminals | RED, YEL & BLU | | |
| Wire Striplength | 0.375 mm | | |
| Lamp Connection | Series | | |
| Wire Length By Color | No wires | | |
| Wire Gauge (Nom) | 18AWG mm | | |
| Wire Type | Solid | | |
| Remote Wiring Configuration Allowed | Yes | | |
| Tandem Wiring Configuration Allowed | Yes | | |
| Through Wiring Configuration Allowed | Yes | | |
| Max Ballast-Lamp Distance Remote Wiring | 1-L = 15' / 2-L = 6' | | |
| Max Ballast-Lamp Distance Tandem Wiring | 2-L: Red = 6' | | |
| Max Ballast-Lamp Distance Through Wiring | 2-L: Red = 6' | | |
| Connector Type | Poke-In | | |
| | | | |
| Temperature | | | |
| T-Case Maximum (Nom) | 75 °C | | |

SmartMate

| Mechanical and Housing | | | |
|--------------------------|-------------------------------------------------|--|--|
| Housing Material | Metal | | |
| Housing | M1 | | |
| Housing Dimensions | 4.98" x 2.4" x 0.98" | | |
| Approval and Application | | | |
| EMC Immunity Standard | FCC Non-Consumer | | |
| Approval Marks | CSA certificate UL certificate CEC Listing RoHS | | |
| | Compliant | | |
| Hum And Noise Level | A | | |
| UL Recognized | No | | |

| Product Data | | | | |
|---------------------------------|----------------------------|--|--|--|
| Order product name | SMARTMATE ICF2S18M1BSQS35M | | | |
| EAN/UPC - Product | 781087059234 | | | |
| Order code | 913710817202 | | | |
| Numerator - Quantity Per Pack | 1 | | | |
| Numerator - Packs per outer box | 16 | | | |
| Material Nr. (12NC) | 913710817202 | | | |
| Net Weight (Piece) | 0.214 kg | | | |

Dimensional drawing



ELE BALLAST (2) 18W CFL 4-PIN 120-277V

| Product | A1 | A2 | A3 | B1 | C1 |
|----------------------------|---------|---------|---------|---------|---------|
| SMARTMATE ICF2S18M1BSQS35M | 4.60 in | 4.20 in | 2.00 in | 2.40 in | 0.98 in |



© 2017 Philips Lighting Holding B.V. All rights reserved. Philips Lighting reserves the right to make changes in specifications and/or to discontinue any product at any timewithout notice or obligation and will not be liable for any consequences resulting from the use of this publication.

www.lighting.philips.com 2017, July 12 - data subject to change