

Presented By: Bulbs Depot

Contact Phone:

Customer Name:

Project Name:

Contact E-mail:

Fixture Type:

**GE**
Lighting**96761 - GE LED 4-Pin Horizontal Plug-in****LED12G24Q-H/835**

- ☞ GE's LED plug-in lamps allow you to replace inefficient CFL 4 pin G24q/GX24 without tools or costly upgrades. Simply plug the replacement lamp into the existing ballast.
- ☞ Uses 50% less energy than CFL (12W LED vs. 26W CFL)
- ☞ These lamps are energy efficient, contain no lead or mercury, and meet the material restriction requirements of RoHS
- ☞ For example, using only 12 watts of energy, save over \$71 in energy costs over the rated life of a lamp versus a standard 26-watt CFL lamp based on \$0.11 per kWh
- ☞ Advanced optics eliminate wasted light to deliver a more targeted beam with fewer lumens (950 vs. 1800)
- ☞ Energy efficiency and long life mean fewer lamp replacements versus CFL light sources
- ☞ Check ballast compatibility at GELighting.com/LED4pin-compatibility

Product Photo**GENERAL CHARACTERISTICS**

Product Technology	LED
Rated Life (Hours)	50000 h
Base	G24q-4

PHOTOMETRIC CHARACTERISTICS

Nominal Initial Lumen per Watt	83.3
Initial Lumens-nominal	1000 lm
Color Rendering Index-CRI	80
Color Temperature	3500 K

PRODUCT INFORMATION

Product Code	96761
Description	LED12G24Q-H/835
Alternative Unit Of Measure	CASE
Standard Package Quantity	
Ean UPC	043168967617
Standard Package GTIN	10043168967614
No Of Items Per Sales Unit	
No Of Items Per Standard Package	
Sales Unit	Case
UCC	043168967617
Alternative Unit Of Measure	EACH
Standard Package Quantity	6
Ean UPC	043168967617
Standard Package GTIN	00043168967617
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	6
Sales Unit	Each
UCC	043168967617

ELECTRICAL CHARACTERISTICS

Voltage <Nom>	120 V
Input Voltage [nom]	120 V

CAUTIONS & WARNINGS**Caution****Risk of Electric Shock**

Suitable for damp locations

Direct replacement for 13W/6T4/Q/G24/PH, 18W/7T4/Q/G24/PH, 26W/8T4/Q/G24/PH CFL lamps only

Not for use with dimmers

For use only with compatible magnetic ballasts. See list at: www.gelighting.com/LED2pin-compatibility

If the lamp does not light when the luminaire is energized, remove lamp from luminaire and contact lamp manufacturer or qualified electrician

If the lamp or luminaire exhibits undesirable operation, such as flickering or buzzing, immediately turn off power, remove lamp from luminaire, and contact manufacturer

Not intended for use with emergency exit lights

Do not use where directly exposed to water

