



Core & Coil (71A) MH ~GT~ 450W

CORE & COIL HID 71A65A2001

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Product data

| General Information | | | | | |
|------------------------------------|--------------------|--|--|--|--|
| ANSI Code | M47 | | | | |
| Lamp Type | 1000W MH | | | | |
| Number Of Lamps | 1 piece/unit | | | | |
| Circuit Type | CWA | | | | |
| Ballast Type | Magnetic HID | | | | |
| Base Model | 71A65A2 | | | | |
| Core Size | 4 1/4 x 6 (2 Coil) | | | | |
| Suitable For Outdoor Use | Yes | | | | |
| Ignitor Catalog Number | NA | | | | |
| Ignitor Temperature Rating | NA | | | | |
| Capacitor Value | 24 MFD | | | | |
| Capacitor Catalog Number | MD2409000 | | | | |
| Capacitor Requirements | 480V | | | | |
| Capacitor Temperature Rating | 90°C | | | | |
| Capacitor Diameter/Oval Dimensions | 1.75 in | | | | |
| Capacitor Height | 3.9 in | | | | |
| Automatic Restart | No | | | | |

| Operating and Electrical | | | |
|-------------------------------------|-------------------------|--|--|
| Input Voltage | 120/277/347 V | | |
| Input Frequency | 60 Hz | | |
| Input Current (Open Circuit) | 4.5/2.2/1.7 A | | |
| Input Current (Starting) | 7.8/3.2/2.5 A | | |
| Input Current (Short Circuit) | 4.8-7.3/2-3.1/1.6-2.6 V | | |
| Secondary Short Circuit Current | 5.2-6.4 A | | |
| Constant Wattage Deviation | 10% | | |
| Ballast Factor (Nom) | 1 | | |
| Power Factor (Nom) | 0.90 | | |
| Open Circuit Voltage | 430 V | | |
| Input Current (Nom) | 9/3.9/3.2 A A | | |
| Input Power (Nom) | 1080 W | | |
| Rated Lamp Power | 1000 W | | |
| | | | |
| Wiring | | | |
| Wire Striplength | 0.5 mm | | |
| Wire Length By Color | 12" | | |
| Wire Type | Stranded | | |
| Remote Wiring Configuration Allowed | Yes | | |


Datasheet, 2016, February 1 data subject to change

Core & Coil (71A) MH ~GT~ 450W

| Max Ballast-Lamp Distance Remote Wiring | Determined by AWG used | | | |
|---|------------------------------------|--|--|--|
| Recommended Fuse Value | 20/10/8 A | | | |
| Approval and Application | | | | |
| Open Circuit Voltage Test (Volts) | 385-475 V | | | |
| Approval Marks | ULR CSA certificate RoHS Compliant | | | |
| Temperature Marking | D/C/C | | | |
| UL Recognized | Yes | | | |
| Hipot Test (1 Minute) | 2000 V | | | |
| Hipot Test (2 Seconds) | 2500 V | | | |
| UL Insulation Class | H(180°C) | | | |
| UL Temperature Code | 1029D | | | |

| Product Data | |
|---------------------------------|----------------------------|
| Order product name | CORE & COIL HID 71A65A2001 |
| EAN/UPC - Product | 781087021958 |
| Order code | 913700525709 |
| Numerator - Quantity Per Pack | 1 |
| Numerator - Packs per outer box | 1 |
| Material Nr. (12NC) | 913700525709 |
| Net Weight (Piece) | 10.156 kg |

Dimensional drawing



MH BAL 1000W M47 120/277/347V KIT

| Product | C1 | C2 | A1 | A2 | A3 | B1 | B2 |
|----------------------------|--------|--------|------|--------|--------|--------|--------|
| CORE & COIL HID 71A65A2001 | 4.5 in | 2.8 in | 6 in | 5.4 in | 4.4 in | 4.3 in | 3.9 in |

