

Optanium T5

OPTANIUM IOP2S28115SC35M

Optanium ballasts for T5 lamps are part of our effort to promote environmental responsibility through Smart Solutions - energy efficient products, lighting systems, services and expertise through Philips Advance branded products.

Product data

General Information Lamp Type F28T5 Number Of Lamps 1/2 piece/unit Ballast Type Electronic Fluorescent Base Model IOP2S28115SC Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.5 s Ballast Factor (Nom) 1.15	
Number Of Lamps 1/2 piece/unit Ballast Type Electronic Fluorescent Base Model IOP2S28115SC Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.6 Ignition Time (Nom) 1.5 s	
Ballast Type Electronic Fluorescent Base Model IOP2S28115SC Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.6 Ignition Time (Nom) 1.5 s	
Base Model IOP2S28115SC Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.6 Ignition Time (Nom) 1.5 s	
Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.6 Ignition Time (Nom) 1.5 s	
Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA Ignition Method Programmed Start Crestfactor (Nom) 1.6 Ignition Time (Nom) 1.5 s	
Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.6 Ignition Time (Nom) 1.5 s	
Input Voltage	
Input Voltage	
Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.6 Ignition Time (Nom) 1.5 s	
Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.6 Ignition Time (Nom) 1.5 s	
Ignition Method Programmed Start Crestfactor (Nom) 1.6 Ignition Time (Nom) 1.5 s	
Crestfactor (Nom) 1.6 Ignition Time (Nom) 1.5 s	
Ignition Time (Nom) 1.5 s	
Ballast Factor (Nom) 1.15	
Power Factor (Nom) 0.98	
Input Current (Max) 0.60 A	
Input Current (Min) 0.26 A	
Input Power (Nom) 71-69 W	
Rated Lamp Power 28 W	

Wiring	
Color Input Terminals	No terminals
Color Output Terminals	No terminals
Wire Striplength	0.50/0.375 mm
Lamp Connection	Series
Wire Length By Color	See data sheet
Wire Gauge (Nom)	18AWG mm
Wire Type	Solid
Remote Wiring Configuration Allowed	Yes
Tandem Wiring Configuration Allowed	Yes
Through Wiring Configuration Allowed	Yes
Max Ballast-Lamp Distance Remote Wiring	20'
Max Ballast-Lamp Distance Tandem Wiring	Any = 20'
Max Ballast-Lamp Distance Through Wiring	Any = 20'
Connector Type	No connector
Temperature	
T-Case Maximum (Nom)	70 °C
Mechanical and Housing	
Housing Material	Metal
Housing	SC


Datasheet, 2016, February 1 data subject to change

Optanium T5

9.5" x 1.7" x 1.18"
FCC Non-Consumer
CSA certificate UL certificate CEC Listing RoHS
Compliant
A
No
OPTANIUM IOP2S28115SC35M

EAN/UPC - Product	781087057667	
Order code	913710815102	
Numerator - Quantity Per Pack	1	
Numerator - Packs per outer box	20	
Material Nr. (12NC)	913710815102	
Net Weight (Piece)	395.000 g	
		_

Dimensional drawing



ELE BALLAST (2) F28T5 120-277V

Product	A1	A2	B1	C1
OPTANIUM IOP2S28115SC35M	9.5 in	8.90 in	1.7 in	1.18 in

