### Presented By: Bulbs Depot

Contact Phone:

**Customer Name:** Project Name:

Contact E-mail: Fixture Type:



Lighting

#### 96799 - GE LED 4-Pin Horizontal Plug-in

### LED12G24Q-H/827

- GE's LED plug-in lamps allow you to replace inefficient CFL 4 pin G24q/GX24 without tools or costly upgrades. Simply plug the replacement lamp into the existing ballast.
- Uses 50% less energy than CFL (12W LED vs. 26W CFL)
- These lamps are energy efficient, contain no lead or mercury, and meet the material restriction requirements of RoHS
- For example, using only 12 watts of energy, save over \$71 in energy costs over the rated life of a lamp versus a standard 26watt CFL lamp based on \$0.11 per kWh
- Advanced optics eliminate wasted light to deliver a more targeted beam with fewer lumens (950 vs. 1800)
- Energy efficiency and long life mean fewer lamp replacements versus CFL light sources
- Check ballast compatability at GELighting.com/LED4pincompatability

## **Product Photo**



### **GENERAL CHARACTERISTICS**

G24Q/GX24 **Base Description** 4-Pin Plug-in Base Type **Primary Application** Indoor Damp **Product Color** White **Product Technology** LED Rated Life (Hours) 50000 h

#### PHOTOMETRIC CHARACTERISTICS

Nominal Initial Lumen per Watt 79.2 Initial Lumens-nominal 950 lm Color Rendering Index-CRI 80 2700 K Color Temperature

### PRODUCT INFORMATION

96799 **Product Code** 

Description LED12G24Q-H/827

Alternative Unit Of Measure **CASE** 

Standard Package Quantity

Ean UPC 043168967990 Standard Package GTIN 10043168967997

No Of Items Per Sales Unit

No Of Items Per Standard Package

Sales Unit Case

UCC 043168967990 Alternative Unit Of Measure **EACH** 

Standard Package Quantity 6

Ean UPC 043168967990 00043168967990 Standard Package GTIN

No Of Items Per Sales Unit 1 No Of Items Per Standard Package 6 Sales Unit Each

UCC 043168967990

## **DIMENSIONS**

Bulb Max Overall Length-MOL 5.31 in

### **ELECTRICAL CHARACTERISTICS**

Rated power (Watts) 12 W

### **CAUTIONS & WARNINGS**

# Caution

Risk of Electric Shock

Suitable for damp locations

Direct replacement for 13W/6T4/Q/G24/PH, 18W/7T4/Q/G24/PH, 26W/8T4/Q/G24/PH CFL lamps only

Not for use with dimmers

For use only with compatible magnetic ballasts. See list at: www.gelighting.com/LED2pin-compatibility

If the lamp does not light when the luminaire is energized, remove lamp from luminaire and contact lamp manufacturer or qualified electrician

If the lamp or luminaire exhibits undesirable operation, such as flickering or buzzing, immediately turn off power, remove lamp from luminaire,

# and contact manufacturer

Not intended for use with emergency exit lights

Do not use where directly exposed to water

Jan 6, 2017 6:19:40 PM For additional information, visit www.gelighting.com