

**Presented By:** iLightDepot  
**Contact Phone:** 513-272-0800  
**Contact E-mail:** sales@ilightdepot.com



**Customer Name:**  
**Project Name:**  
**Fixture Type:**



GE  
Lighting

### 97613 - F26DBX/841/ECO4P

GE Ecolux® Biax® T4 - Facilities; Retail Display; Hospitality; Office; Restaurant; Warehouse



#### GENERAL CHARACTERISTICS

Lamp Type	Compact Fluorescent - Plug-In
Bulb	T4
Base	G24q-3
Rated Life	17000.0 hrs
Starting Temperature (MIN)	0.0 °C
Cathode Resistance	2.7 Ohm
LEED-EB MR Credit	115 picograms Hg per mean lumen hour
Rated Life (rapid start) @ Time	20000.0 @ 12.0 h
Additional Info	Dimmable with appropriate dimming ballast./End of Life Protection (EOL)/TCLP compliant
Primary Application	Facilities;Retail Display;Hospitality;Office;Restaurant;Warehouse

#### PHOTOMETRIC CHARACTERISTICS

Initial Lumens	1800.0
Mean Lumens	1530.0
Nominal Initial Lumens per Watt	69
Color Temperature	4100.0 K
Color Rendering Index (CRI)	82.0

#### ELECTRICAL CHARACTERISTICS

Wattage	26.0
Voltage	120.0
Current (max)	5.25 A
Open Circuit Voltage (after preheating) (MAX)	240.0 V
Open Circuit Voltage Across Starter (MIN)	198.0 V
Lamp Current	0.325 A
Preheat Voltage (MIN)	4.25 V
Current Crest Factor (MAX)	1.7
Supply Current Frequency	60.0 Hz

#### DIMENSIONS

Maximum Overall Length (MOL)	6.4000 in(162.6 mm)
Nominal Length	6.400 in(162.6 mm)
Base Face to Top of Lamp	5.800 in(147.3 mm)

#### PRODUCT INFORMATION

Product Code	97613
Description	F26DBX/841/ECO4P
ANSI Code	60901-IEC-2562-2
Standard Package	BUNDLE
Standard Package GTIN	
Standard Package Quantity	50
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	50
UPC	043168976138

#### CAUTIONS & WARNINGS

##### Caution

- Lamp may shatter and cause injury if broken
  - Remove and install by grasping only plastic portion of the lamp.

#### NOTES

- 4-Pin lamp minimum starting temperature is a function of the ballast. Most ballasts are rated with a minimum starting temperature of 50 degrees F (10 C). Ballasts are also available that provide reliable starting to 0 degrees F (-18C) and -20 F (-29C).

- Based on 60Hz reference circuit.

- Fluorescent lamp lumens decline during life

Jul 6, 2012 11:01:37 AM

For additional information, visit [www.gelighting.com](http://www.gelighting.com)