

Presented By: BulbsDepot.com
Contact Phone:
Contact E-mail:

Customer Name:
Project Name:
Fixture Type:



GE
Lighting

72275 - GE232MAX-G-N (Replaces GE-232-MV-N)

GE UltraMax® General Series T8 Electronic Multivolt Instant Start Ballast

- High performance electronic ballast for all general fluorescent applications
- Instant start electronic ballast for long lamp starting cycles and low initial cost
- Multi-Voltage Technology handles voltage from 120 to 277V
- Light-weight, Low Profile Housing
- Parallel lamp operation means system maintenance is easier to manage
- Anti-striation Control for better light quality, with no striations

GENERAL CHARACTERISTICS

Application	2 or 1- F32T8 120 to 277 "N".87 BF
Category	Linear Fluorescent
Ballast Type	Electronic - Multivolt Instant Start
Starting Method	Instant start
Lamp Wiring	Parallel
Line Voltage Regulation (+/-) (NOM)	10.0 %
Ambient Temperature (MIN)	-22.0 °F
Ambient Temperature (MAX)	104.0 °F (40 °C)
Case Temperature (MAX)	70.0 °C
Ballast Factor	Normal
Power Factor Correction	Active
Sound Rating	A (20-24 decibels)
Additional Info	Auto-restart / Thermally protected / Anti-striation control

PRODUCT INFORMATION

Product Code	72275
Description	GE232MAX-G-N (Replaces GE-232-MV-N)
Standard Package	Case
Standard Package GTIN	10043168722756
Standard Package Quantity	10
Sales Unit	Standard Pack
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	10
UPC	043168722759

DIMENSIONS

Case dimensions			
Length (L)		9.5 in(241.30 mm)	
Width (W)		1.3 in(33.02 mm)	
Height (H)		1.2 in(29.97 mm)	
Mounting dimensions			
Bracket Length (BL)		NaN in(NaN mm)	
Mount Length (M)		8.9 in(226.06 mm)	
Mount Width (X or F)		1.1 in(27.94 mm)	
Mount Slots (MS)		0.3 in(7.62 mm)	
Weight (NOM)		1.4 lb	
Exit Type		Side	
Remote Mounting Distance (NOM)		18.0 ft	
Remote Mounting Wire Gauge (NOM)		18.0 AWG	
Lead lengths	Qty	Exit	Length (± 1 in.)
Black	1	Left	25 (635 mm)
Red	1	Right	45 (1143 mm)
White	1	Left	25 (635 mm)
Blue	2	Right	31 (787 mm)

ELECTRICAL CHARACTERISTICS

Supply Current Frequency (MIN)	50.0 Hz
Supply Current Frequency (NOM)	60.0 Hz / 50.0 Hz

SAFETY & PERFORMANCE

- cUL Listed
- FCC - CLASS A Non-Consumer
- NRCan
- UL Class P
- UL Listed
- UL Type 1 Outdoor
- UL Type HL
- NEMA Premium®
- Product is compliant with material restriction requirements of RoHS

SPECIFICATIONS BY LAMP & WATTAGE

Lamp	# of Lamps	Line Volts	System Watts	Nom. Line Current	System Ballast Factor	Ballast Efficacy Factor	Power Factor% (>=)	Crest Factor (<=)	THD% (<=)	Min. Starting Temp (°F/°C)
F40T8	1	120	44	0.37 A	1.08	2.45	99	1.7	5.0	-22.0 °F / NaN
F40T8	1	277	43	0.16 A	1.08	2.51	96	1.7	8.0	-22.0 °F / NaN
F32T8/WM	1	120	33	0.28 A	1.05	3.18	99	1.7	6.0	60.0 °F / NaN
F32T8/WM	1	277	33	0.12 A	1.05	3.18	96	1.7	8.0	60.0 °F / NaN
F32T8/WM	2	120	53	0.44 A	0.86	1.62	99	1.7	4.0	60.0 °F / NaN
F32T8/WM	2	277	51	0.19 A	0.87	1.71	97	1.7	8.0	60.0 °F / NaN
F32T8/25W	1	120	28	0.0 A	1.02	3.64	99	1.7	10.0	60.0 °F / NaN
F32T8/25W	1	277	28	0.0 A	1.02	3.64	98	1.7	10.0	60.0 °F / NaN
F32T8/25W	2	120	43	0.0 A	0.86	1.93	99	1.7	10.0	60.0 °F / NaN
F32T8/25W	2	277	43	0.0 A	0.86	1.93	97	1.7	10.0	60.0 °F / NaN
F32T8	1	120	35	0.3 A	1.08	3.09	99	1.7	5.0	-22.0 °F / NaN
F32T8	1	277	35	0.13 A	1.08	3.09	97	1.7	8.0	-22.0 °F / NaN
F32T8	2	120	56	0.48 A	0.89	1.59	99	1.7	4.0	-22.0 °F / NaN
F32T8	2	277	55	0.2 A	0.88	1.60	98	1.7	9.0	-22.0 °F / NaN
F28T8	1	120	31	0.26 A	1.02	3.29	99	1.7	6.0	60.0 °F / NaN
F28T8	1	277	31	0.11 A	1.02	3.29	95	1.7	9.0	60.0 °F / NaN
F28T8	2	120	47	0.39 A	0.83	1.77	99	1.7	4.0	60.0 °F / NaN
F28T8	2	277	47	0.17 A	0.83	1.77	97	1.7	8.0	60.0 °F / NaN
F25T8	1	120	28	0.23 A	1.08	3.86	99	1.7	7.0	-22.0 °F / NaN
F25T8	1	277	28	0.11 A	1.08	3.86	95	1.7	9.0	-22.0 °F / NaN
F25T8	2	120	44	0.37 A	0.90	2.05	99	1.7	5.0	-22.0 °F / NaN
F25T8	2	277	44	0.16 A	0.91	2.07	97	1.7	7.0	-22.0 °F / NaN
F17T8	1	120	20	0.17 A	1.05	5.25	99	1.7	8.0	-22.0 °F / NaN
F17T8	1	277	21	0.08 A	1.05	5.00	92	1.7	14.0	-22.0 °F / NaN
F17T8	2	120	31	0.26 A	0.88	2.84	99	1.7	6.0	-22.0 °F / NaN
F17T8	2	277	31	0.12 A	0.88	2.84	95	1.7	9.0	-22.0 °F / NaN

CAUTIONS & WARNINGS

Warning

- Risk of Electric Shock
 - Properly ground ballast and fixture.
 - Turn power off before servicing--see instructions.

WARRANTY INFORMATION

GE Lighting warrants to the purchaser that each ballast will be free from defects in material or workmanship for period as defined in the attached documents from the date of manufacture when properly installed and under normal conditions of use.