

# NHRIC-6LMRAT

6" IC Air-Tight LED Dedicated Remodel Housing  
(Compatible with Cobalt / Marquise / Onyx / PRISM)

Type	
Project	
Catalog No.	
Notes	

## PRODUCT DESCRIPTION

Dedicated remodel housing for use in insulated ceilings can be in direct contact with insulation.\* Air-tight construction provides energy savings by reducing the flow of air through the ceiling. The housing is dedicated and labeled for use with LED retrofit luminaires.

## FEATURES

- IC Air-Tight energy saving by reducing the flow of air through the ceiling
- Rated for direct contact with insulation
- Installation-ready for existing sheet rock ceilings

## CONSTRUCTION

**Housing:** 0.040 steel housing adjusts to a maximum ceiling thickness of 1-5/8". Housing terminates at a 1/4" ceiling flange for even positioning of housing angle within the ceiling. Structural arm consists of 0.050 steel and connects to housing with junction box. Integral spring brackets provided.

**Air Flow Restriction:** Meets requirements of Air-Tight (AT) <2CFM (cubic feet per minute) in accordance with ASTM-283 Air-Tight requirements.

**Clearance:** "IC" Insulated ceiling housings are direct contact rated. Not to be used in direct contact with spray foam insulation.

**Mounting:** Four high tension tempered steel springs secure remodel housing to 1-5/8" thick (max.) ceiling (Hole cutout template provided for convenience)

**Junction Box:** Prewired 15 cubic inch 0.064" thick galvanized steel with four 1/2" trade size knockouts, one 3/4" trade size knockout, four Romex® pryouts, and snap on covers. All leads are #18AWG wire, the ground wire is connected to the bottom, and quick connectors are supplied on all leads. Maximum of 6 no. 12 AWG through branch circuit conductors suitable for at least 90°C permitted in junction box.

## ELECTRICAL

**Input Voltage:** 120/277V

**Socket:** Quick connect for LED luminaires

**Operating Temperature:** 122°F (50°C) max.

**Dimming:** Specified by luminaire

## STEP DOWN TRANSFORMER (CONVERTS 277V INPUT TO 120V)

Optional 50W step down transformer installed (NHRIC-6LMRAT/277)

## COMPATIBILITY

- [NRMIC-61](#) - 6" Marquise I Reflector
- [NRMIC-62](#) - 6" Marquise I Baffle
- [NRMIC2-61](#) - 6" Marquise II Reflector
- [NRMIC2-62](#) - 6" Marquise II Baffle
- [NLCBC-6 / NLCBC2-6](#) - 6" Cobalt Series
- [NOX-56 / NOXAC-56 / NOXTW-56](#) - 5"7/8" Onyx Series
- [NOX-636](#) - 6" Onyx Square Reflector
- [NLPR-5641](#) - 5"7/8" PRISM Reflector
- [NLPR-5642](#) - 5"7/8" PRISM Baffle

## EMERGENCY (NEPK-07LEDUNV)



Remote 90-minute battery back-up and remote test switch can be specified and installed separately.

## LABELS AND LISTINGS

- cULus Listed for damp location & feed through (wet location when used with compatible reflectors)
- WSEC ASTM E283 for Air-Tight
- RoHS Compliant
- Certified to the high efficacy requirements of California Title 24 JA8-2019



## PRODUCT IMAGES & DIMENSIONS



## 6" IC Air-Tight LED Dedicated Remodel Housing

Housing Type

**NHRIC-6LMRAT** = 6" IC Air-Tight Remodel Housing, 120/277V input (120V Triac/ELV dimming)

**NHRIC-6LMRAT/277** = 6" IC Air-Tight Remodel Housing, 277V input with 50W Step Down Transformer

**NHRIC-6LMRAT/4W** = 6" IC Air-Tight Remodel Housing, 120/277V input (120V Triac/ELV/0-10V & 277V 0-10V dimming, Cobalt only - LE4 required)

**NHRIC-6LMRAT/PEM** = 6" IC Air-Tight Remodel Housing with Pre-Wiring for Emergency, 120/277V input (Cobalt only - EM required)

**NHRIC-6LMRAT/6WPPEM** = 6" IC Air-Tight Remodel Housing with Pre-Wiring for Emergency, 120/277V input (120V Triac/ELV/0-10V & 277V 0-10V dimming, Cobalt only - LE4EM required)

Example: **NHRIC-6LMRAT** = 6" IC Air-Tight LED Dedicated Remodel Housing, 120/277V input