

69115 - GE LED A19

LED6DA19/827 120

- ☞ Energy efficiency and long life mean fewer lamp replacements versus standard incandescent or halogen light sources
- ☞ 40 watt replacement using only 6 watts
- ☞ Light pattern similar to traditional incandescent bulbs.
- ☞ Great for frequently used fixtures
- ☞ Omnidirectional
- ☞ Energy Star Rated

PRODUCT PHOTO



GENERAL CHARACTERISTICS

Base Description	Medium Screw
Base Type	Screw-In
Dimmable	Yes
Lamp Type	A19
Primary Application	General Purpose
Product Color	White
Product Technology	LED
Rated Life - Min	15000 h
Rated Life (Hours)	15000 h
Dimmable / Non-Dimmable	Yes
Lamp Count	1
Life in Years	13.7 yr
Requested Structure	Carton
Estimated Energy Cost per Year	0.72
Bulb Shape	A19

PHOTOMETRIC CHARACTERISTICS

Nominal Initial Lumen per Watt	80
Initial Lumens-nominal	480 lm
Color Rendering Index-CRI	80
Color Temperature	2700 K

PRODUCT INFORMATION

Product Code	69115
Description	LED6DA19/827 120
Alternative Unit Of Measure	EACH
Standard Package Quantity	1
Ean UPC	043168691154
Standard Package GTIN	00043168691154
No Of Items Per Sales Unit	
No Of Items Per Standard Package	1
Sales Unit	Each
UCC	
Alternative Unit Of Measure	CASE
Standard Package Quantity	6
Ean UPC	043168691154
Standard Package GTIN	10043168691151
No Of Items Per Sales Unit	
No Of Items Per Standard Package	6
Sales Unit	Case
UCC	

DIMENSIONS

Bulb Max Overall Length-MOL	4.4 in
-----------------------------	--------

ELECTRICAL CHARACTERISTICS

Drive Current	13.7
Energy Efficiency Class	yr
Voltage <Nom>	120 V
Rated power (Watts)	6 W

CAUTIONS & WARNINGS

Caution

Risk of Electric Shock

- Suitable for damp locations
- Not for use in totally enclosed luminaires
- Not intended for use with emergency exit fixtures or emergency exit lights
- Performance may vary with electronic timers / photocells or dimmers
- Suitable for damp locations
- Not for use in totally enclosed luminaires
- Not intended for use with emergency exit fixtures or emergency exit lights

Performance may vary with electronic timers / photocells or dimmers

Apr 19, 2021 8:07:22 PM | For additional information, visit <https://products.gecurrent.com/>